



Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Revised: May 29, 2014



Note

For the clearest readability of these tables, please use the PDF version provided in the upper right side of your browser screen. The HTML version may have confusing alignment of table data.



Note

Requirements and procedures for initial configurations and software upgrades tend to change and therefore appear only in the switch or router software release notes. Before installing, configuring, or upgrading a switch, refer to the product release notes on Cisco.com for the latest information. This matrix does not replace or supersede the release notes.

This publication contains information on the Cisco platforms and minimum software releases that support the Gigabit Interface Converter (GBIC) and Gigabit Ethernet Small Form-Factor Pluggable (SFP) transceiver modules. [Table 1](#) lists the Gigabit Ethernet transceiver model numbers and operating wavelengths. The other tables are as follows:

- [Table 2, Catalyst Express 500 Support](#)
- [Table 3, Metro Ethernet Support](#)
- [Table 4, Catalyst 2900 Switches Support](#)
- [Table 5, Catalyst 3500 Switches Support](#)
- [Table 6, Catalyst 3600 Series Switches Support](#)
- [Table 7, Catalyst 3700 Series Switches Support](#)
- [Table 8, Catalyst 3800 Series Switches Support](#)
- [Table 9, Industrial Ethernet and Smart Grid Support](#)
- [Table 10, Catalyst 4500 and Catalyst 4900 Switches Support](#)
- [Table 11, Catalyst 6500 Series Switches Support](#)
- [Table 12, Catalyst 6800 Series Switches Support](#)
- [Table 13, Data Center and Blade Switching Support](#)



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

- [Table 14, Router Support](#)
- [Table 15, Appliance Support](#)
- [Table 16, Wireless LAN Controllers Support](#)

Table 1 Gigabit Ethernet Transceiver Models

Model Number	Description
GBIC Transceivers	
WS-G5482=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5483=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5484=	1000BASE-SX GBIC transceiver module for Multi mode Fiber (MMF), 850-nanometer (nm) wavelength, dual SC/PC connector
WS-G5486=	1000BASE-LX/LH GBIC transceiver module for MMF and SMF, 1300-nm wavelength, dual SC/PC connector
WS-G5487=	1000BASE-ZX GBIC transceiver module for Single Mode Fiber (SMF), 1550-nm wavelength, dual SC/PC connector
CWDM GBIC Transceivers (Dual SC/PC connectors)	
CWDM-GBIC-1470=	Cisco 1000BASE-CWDM GBIC 1470 nm
CWDM-GBIC-1490=	Cisco 1000BASE-CWDM GBIC 1490 nm
CWDM-GBIC-1510=	Cisco 1000BASE-CWDM GBIC 1510 nm
CWDM-GBIC-1530=	Cisco 1000BASE-CWDM GBIC 1530 nm
CWDM-GBIC-1550=	Cisco 1000BASE-CWDM GBIC 1550 nm
CWDM-GBIC-1570=	Cisco 1000BASE-CWDM GBIC 1570 nm
CWDM-GBIC-1590=	Cisco 1000BASE-CWDM GBIC 1590 nm
CWDM-GBIC-1610=	Cisco 1000BASE-CWDM GBIC 1610 nm
DWDM GBIC Transceivers (Dual SC/PC connectors)	
DWDM-GBIC-60.61=	1000BASE-DWDM GBIC 1560.61 nm
DWDM-GBIC-59.79=	1000BASE-DWDM GBIC 1559.79 nm
DWDM-GBIC-58.98=	1000BASE-DWDM GBIC 1558.98 nm
DWDM-GBIC-58.17=	1000BASE-DWDM GBIC 1558.17 nm
DWDM-GBIC-56.55=	1000BASE-DWDM GBIC 1556.55 nm
DWDM-GBIC-55.75=	1000BASE-DWDM GBIC 1555.75 nm
DWDM-GBIC-54.94=	1000BASE-DWDM GBIC 1554.94 nm
DWDM-GBIC-54.13=	1000BASE-DWDM GBIC 1554.13 nm
DWDM-GBIC-52.52=	1000BASE-DWDM GBIC 1552.52 nm
DWDM-GBIC-51.72=	1000BASE-DWDM GBIC 1551.72 nm
DWDM-GBIC-50.92=	1000BASE-DWDM GBIC 1550.92 nm

Table 1 Gigabit Ethernet Transceiver Models (continued)

Model Number	Description
DWDM GBIC Transceivers (continued)	
DWDM-GBIC-50.12=	1000BASE-DWDM GBIC 1550.12 nm
DWDM-GBIC-48.51=	1000BASE-DWDM GBIC 1548.51 nm
DWDM-GBIC-47.72=	1000BASE-DWDM GBIC 1547.72 nm
DWDM-GBIC-46.92=	1000BASE-DWDM GBIC 1546.92 nm
DWDM-GBIC-46.12=	1000BASE-DWDM GBIC 1546.12 nm
DWDM-GBIC-44.53=	1000BASE-DWDM GBIC 1544.53 nm
DWDM-GBIC-43.73=	1000BASE-DWDM GBIC 1543.73 nm
DWDM-GBIC-42.94=	1000BASE-DWDM GBIC 1542.94 nm
DWDM-GBIC-42.14=	1000BASE-DWDM GBIC 1542.14 nm
DWDM-GBIC-40.56=	1000BASE-DWDM GBIC 1540.56 nm
DWDM-GBIC-39.77=	1000BASE-DWDM GBIC 1539.77 nm
DWDM-GBIC-39.98=	1000BASE-DWDM GBIC 1539.98 nm
DWDM-GBIC-38.19=	1000BASE-DWDM GBIC 1538.19 nm
DWDM-GBIC-35.82=	1000BASE-DWDM GBIC 1535.82 nm
DWDM-GBIC-35.04=	1000BASE-DWDM GBIC 1535.04 nm
DWDM-GBIC-34.25=	1000BASE-DWDM GBIC 1534.25 nm
DWDM-GBIC-32.68=	1000BASE-DWDM GBIC 1532.68 nm
DWDM-GBIC-31.90=	1000BASE-DWDM GBIC 1531.90 nm
DWDM-GBIC-31.12=	1000BASE-DWDM GBIC 1531.12 nm
DWDM-GBIC-30.33=	1000BASE-DWDM GBIC 1530.33 nm
SFP Transceivers	
GLC-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, RJ-45 connector
GLC-SX-MM=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, dual LC/PC connector
GLC-LH-SM=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, dual LC/PC connector
GLC-ZX-SM=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
GLC-BX-D=	1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, single LC/PC connector
GLC-BX-U=	1000BASE-BX10 SFP module for single-strand SMF, 1310-nm TX/1490-nm RX wavelength, single LC/PC connector
GLC-2BX-D=	Dual-channel 1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, two single LC/PC connectors

Table 1 Gigabit Ethernet Transceiver Models (continued)

Model Number	Description
SFP Transceivers (continued)	
SFP-GE-S=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-L=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-EX-SMD=	1000BASE-EX SFP transceiver module for SMF, 1310-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-Z=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, extended operating temperature range, RJ-45 connector
GLC-SX-MM-RGD	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-LX-SM-RGD	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-ZX-SM-RGD	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-SX-MMD=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-LH-SMD=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-ZX-SMD=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
SFP-GPON-B	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-B-I	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range
SFP-GPON-C	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-C-I	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range

Table 1 Gigabit Ethernet Transceiver Models (continued)

Model Number	Description
CWDM SFP Transceivers (dual LC/PC connector)	
CWDM-SFP-1470=	Cisco CWDM SFP 1470 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1490=	Cisco CWDM SFP 1490 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1510=	Cisco CWDM SFP 1510 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1530=	Cisco CWDM SFP 1530 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1550=	Cisco CWDM SFP 1550 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1570=	Cisco CWDM SFP 1570 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1590=	Cisco CWDM SFP 1590 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1610=	Cisco CWDM SFP 1610 nm; Gigabit Ethernet and 1G/2G FC
DWDM SFP Transceivers (dual LC/PC connector)	
DWDM-SFP-6061=	Cisco 1000BASE-DWDM SFP 1560.61 nm
DWDM-SFP-5979=	Cisco 1000BASE-DWDM SFP 1559.79 nm
DWDM-SFP-5898=	Cisco 1000BASE-DWDM SFP 1558.98 nm
DWDM-SFP-5817=	Cisco 1000BASE-DWDM SFP 1558.17 nm
DWDM-SFP-5655=	Cisco 1000BASE-DWDM SFP 1556.55 nm
DWDM-SFP-5575=	Cisco 1000BASE-DWDM SFP 1555.75 nm
DWDM-SFP-5413=	Cisco 1000BASE-DWDM SFP 1554.13 nm
DWDM-SFP-5494=	Cisco 1000BASE-DWDM SFP 1554.94 nm
DWDM-SFP-5252=	Cisco 1000BASE-DWDM SFP 1552.52 nm
DWDM-SFP-5172=	Cisco 1000BASE-DWDM SFP 1551.72 nm
DWDM-SFP-5092=	Cisco 1000BASE-DWDM SFP 1550.92 nm
DWDM-SFP-5012=	Cisco 1000BASE-DWDM SFP 1550.12 nm
DWDM-SFP-4851=	Cisco 1000BASE-DWDM SFP 1548.51 nm
DWDM-SFP-4772=	Cisco 1000BASE-DWDM SFP 1547.72 nm
DWDM-SFP-4692=	Cisco 1000BASE-DWDM SFP 1546.92 nm
DWDM-SFP-4612=	Cisco 1000BASE-DWDM SFP 1546.12 nm
DWDM-SFP-4453=	Cisco 1000BASE-DWDM SFP 1544.53 nm
DWDM-SFP-4373=	Cisco 1000BASE-DWDM SFP 1543.73 nm
DWDM-SFP-4294=	Cisco 1000BASE-DWDM SFP 1542.94 nm
DWDM-SFP-4214=	Cisco 1000BASE-DWDM SFP 1542.14 nm
DWDM-SFP-4056=	Cisco 1000BASE-DWDM SFP 1540.56 nm
DWDM-SFP-3977=	Cisco 1000BASE-DWDM SFP 1539.77 nm
DWDM-SFP-3898=	Cisco 1000BASE-DWDM SFP 1539.98 nm
DWDM-SFP-3819=	Cisco 1000BASE-DWDM SFP 1538.19 nm
DWDM-SFP-3661=	Cisco 1000BASE-DWDM SFP 1536.61 nm
DWDM-SFP-3582=	Cisco 1000BASE-DWDM SFP 1535.82 nm

Table 1 Gigabit Ethernet Transceiver Models (continued)

Model Number	Description
DWDM SFP Transceivers (continued)	
DWDM-SFP-3504=	Cisco 1000BASE-DWDM SFP 1535.04 nm
DWDM-SFP-3425=	Cisco 1000BASE-DWDM SFP 1534.25 nm
DWDM-SFP-3268=	Cisco 1000BASE-DWDM SFP 1532.68 nm
DWDM-SFP-3190=	Cisco 1000BASE-DWDM SFP 1531.90 nm
DWDM-SFP-3112=	Cisco 1000BASE-DWDM SFP 1531.12 nm
DWDM-SFP-3033=	Cisco 1000BASE-DWDM SFP 1530.33 nm
DWDM SFP Transceivers (8 additional wavelengths) (dual LC/PC connector)	
DWDM-SFP-6141=	Cisco 1000BASE-DWDM SFP 1561.42 nm
DWDM-SFP-5736=	Cisco 1000BASE-DWDM SFP 1557.36 nm
DWDM-SFP-5332=	Cisco 1000BASE-DWDM SFP 1553.33 nm
DWDM-SFP-4931=	Cisco 1000BASE-DWDM SFP 1549.32 nm
DWDM-SFP-4532=	Cisco 1000BASE-DWDM SFP 1545.32 nm
DWDM-SFP-4134=	Cisco 1000BASE-DWDM SFP 1541.35 nm
DWDM-SFP-3739=	Cisco 1000BASE-DWDM SFP 1537.40 nm
DWDM-SFP-3346=	Cisco 1000BASE-DWDM SFP 1533.47 nm

Table 2 Catalyst Express 500 Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst Express 500	WS-CE500-24LC	GLC-SX-MM	—	12.2(25)FY
	WS-CE500-24PC	GLC-LH-SM		
	WS-CE500G-12TC	GLC-SX-MMD GLC-LH-SMD		
Catalyst Express 520	WS-CE520-8PC-K9	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(35)EX
	WS-CE520-24LC-K9 WS-CE520-24PC-K9 WS-CE520G-24TC-K9	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD		

Table 3 Metro Ethernet Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 2400	ME-2400-24TS-A ME-2400-24TS-D	GLC-T(10/100/1000) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	12.2(25)EX
		GLC-BX-D GLC-BX-U CDWM SFP	12.2(44)SE	12.2(25)EX
Cisco ME2600X	ME2600X-44FA-D-K9= ME2600X-44FE-D-K9= ME2600X-44FA-A-K9=	GLC-BX-D GLC-BX-U	—	15.2(02)SA
Cisco ME 3400	ME-3400-24TS-A ME-3400-24TS-D	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(25)EX
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(25)EX
		GLC-ZX-SM	12.2(46)SE	12.2(25)EX
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(44)SE	12.2(25)EX
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Table 3 *Metro Ethernet Support (continued)*

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 3400 (continued)	ME-3400G-12CS-A ME-3400G-12CS-D	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(25)SEG1
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(25)SEG1
		GLC-ZX-SM	12.2(46)SE	12.2(25)SEG1
		GLC-BX-D	12.2(44)SE	12.2(25)SEG1
		GLC-BX-U	12.2(44)SE	12.2(25)SEG1
		CWDM SFP	12.2(44)SE	12.2(25)SEG1
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
	GLC-EX-SMD	12.2(52)SE	12.2(52)SE	
	ME-3400G-2CS-A	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(35)SE1
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM	12.2(46)SE	12.2(35)SE1
		GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(35)SE1
		CWDM SFP	12.2(44)SE	12.2(35)SE1
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Table 3 Metro Ethernet Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 3400 (continued)	ME-3400-24FS-A	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(40)SE
		GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(40)SE
		GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(40)SE
		CWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP	12.2(50)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
	ME-3400E-24TS-M ME-3400EG-2CS-A ME-3400EG-12CS-M	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(44)EY
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(44)EY	12.2(44)EY
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE

Table 3 Metro Ethernet Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750 Metro	ME-C3750-24TE-M	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	—	12.1(14)AX
		GLC-ZX-SM	12.2(46)SE	12.1(14)AX1
		CWDM SFP	12.2(44)SE	12.1(14)AX1
		GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(25)EY2
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	—	12.2(46)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-EX-SMD	12.2(52)SE	12.2(52)SE
		Cisco ME 3600X	ME-3600X-24FS-M (SFP ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)
GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-U (CPN 10-2094-02) GLC-BX-D (CPN 10-2093-02)	12.2(52)EY			12.2(52)EY
CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD GLC-ZX-SM	15.1(2)EY			15.1(2)EY

Table 3 Metro Ethernet Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 3600X (continued)	ME-3600X-24FS-M ME-3600X-24TS-M (SFP+ ports)	GLC-SX-MM GLC-LH-SM	—	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
	ME-3600X-24CX-M	SFP-GE-Z	15.3(1)S	15.3(1)S
		GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-SX-MMD GLC-EX-SMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-L SFP-GE-S GLC-LH-SM GLC-SX-MM GLC-T SFP-GE-T GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)S1	15.2(2)S1

Table 3 Metro Ethernet Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 3800X	ME-3800X-24FS-M (client ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)	—	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
	ME-3800X-24FS-M (SFP+ ports)	GLC-SX-MM GLC-LH-SM	—	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
Cisco ME 4600 Series	ME4600-AMX-16GPON	SFP-GPON-B SFP-GPON-B-I SFP-GPON-C SFP-GPON-C-I	3.3.1	3.3.1
	ME4600-AMX-48GE	GLC-BX-D GLC-BX-U GLC-2BX-D	3.3.1	3.3.1
Cisco ME 4900 Series	ME-4924-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(31)SGA
		GLC-ZX-SMD GLC-BX-D GLC-BX-U CDWM SFP	12.2(31)SGA	12.2(31)SGA
		DWDM SFP	12.2(37)SG	12.2(37)SG

Table 3 *Metro Ethernet Support (continued)*

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco ME 6500 Series	ME-C6524GS-8S ME-C6524GT-8S	GLC-T (1000BASE-T)	—	12.2(18)ZU
		GLC-SX-MM		
		GLC-LH-SM		
		GLC-ZX-SM		
		GLC-BX-D		
		GLC-BX-U		
		CDWM SFP		
		GLC-SX-MMD		
		GLC-LH-SMD		
		GLC-ZX-SMD		
		GLC-T (10/100/1000)	—	12.2(33)SXH
		DWDM SFP	—	12.2(18)ZU2

Table 4 Catalyst 2900 Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2900 series	WS-C2980G-A	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2.1	—
	WS-C2948G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	—
	WS-C2948G-L3	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	—
	WS-C2948G-GE-TX	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP	8.2(1)GLX	—
	WS-C2912MF-XL with WS-X2931-XL	WS-G5482	—	12.0(5)XW
		WS-G5483 WS-G5484 WS-G5486 WS-G5487	—	12.0(5)WC3b
		CWDM GBIC	—	12.0(5)WC5
	WS-C2924M-XL-EN with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486 WS-G5487	—	12.0(5)WC3b
		CWDM GBIC		12.0(5)WC5
	WS-C2924M-XL-EN-DC with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486 WS-G5487	—	12.0(5)WC3b
CWDM GBIC		—	12.0(5)WC5	

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2940 Series	WS-C2940-8TF-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.1(13)AY
Catalyst 2950 Series	WS-C2950G-12-EI WS-C2950G-24-EI WS-C2950G-24-EI-DC WS-C2950G-48-EI	WS-G5483	—	12.1(6)EA2b
		WS-G5484	—	12.1(6)EA2b
		WS-G5486 WS-G5487	—	12.1(6)EA2b
		CWDM GBIC	—	12.1(12c)EA1
	DWDM GBIC	—	12.1(20)EA2	
	WS-C2950ST-8 LRE WS-C2950ST-24 LRE WS-C2950ST-24 LRE997	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.1(19)EA1c

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960 series	WS-C2960-24TC-L WS-C2960G-24TC-L WS-C2960-48TC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(25)FX
	WS-C2960-24PC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(44)SE
	WS-C2960-24TC-S WS-C2960-48TC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(37)EY
	WS-C2960-8TC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(46)SE

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960 series (continued)	WS-C2960-48PST-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(46)SE
	WS-C2960-8TC-L WS-C2960G-8TC-L	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(35)SE
	WS-C2960G-48TC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(25)SEE
	WS-C2960-48PST-S WS-C2960-24PC-S WS-C2960-24LC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(50)SE

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960-Plus Series	WS-C2960+48PST-L WS-C2960+24PC-L WS-C2960+24LC-L WS-C2960+48TC-L WS-C2960+24TC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(2)EZ
	WS-C2960+48PST-S WS-C2960+24PC-S WS-C2960+24LC-S WS-C2960+48TC-S WS-C2960+24TC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	15.0(2)EZ
Catalyst 2960-S Series	WS-C2960S-24TS-S WS-C2960S-48TS-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SM	—	12.2(53)SE1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	IOS 12.2(58)SE
	WS-C2960S-48FPS-L WS-C2960S-48LPS-L WS-C2960S-24PS-L WS-C2960S-48TS-L WS-C2960S-24TS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(53)SE1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	IOS 12.2(58)SE

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960-S Series (continued)	WS-C2960S-48FPD-L WS-C2960S-48LPD-L WS-C2960S-24PD-L WS-C2960S-48TD-L WS-C2960S-24TD-L	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(53)SE1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	IOS 12.2(58)SE
Catalyst 2960-SF Series	2960S-F48TS-S 2960S-F24TS-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE
	2960S-F48FPS-L 2960S-F48LPS-L 2960S-F24PS-L 2960S-F48TS-L 2960S-F24TS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960-C Series	WS-C2960CG-8TC-L	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP	—	12.2(55)EX1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE
	WS-C2960C-8TC-S	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD	—	12.2(55)EX3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE
	WS-C2960C-8TC-L WS-C2960C-8PC-L WS-C2960C-12PC-L	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP	—	12.2(55)EX3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE
Catalyst 2960-X Series	WS-C2960X-24TS-LL WS-C2960X-48TS-LL	GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-T GLC-LH-SM GLC-SX-MM	15.0(2)EX	15.0(2)EX

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2960-X Series (continued)	WS-C2960X-24PSQ-L	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM	15.0(2)EX	15.0(2)EX
	WS-C2960X-24PS-L WS-C2960X-24TS-L WS-C2960X-48TS-L WS-C2960X-48LPS-L WS-C2960X-48FPS-L WS-C2960X-24TD-L WS-C2960X-24PD-L WS-C2960X-48TD-L WS-C2960X-48LPD-L WS-C2960X-48FPD-L	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM CWDM-SFP	15.0(2)EX	15.0(2)EX
Catalyst 2960-XR Series	WS-C2960XR-24TS-I WS-C2960XR-48TS-I WS-C2960XR-24PS-I WS-C2960XR-48LPS-I WS-C2960XR-48FPS-I WS-C2960XR-24TD-I WS-C2960XR-48TD-I WS-C2960XR-24PD-I WS-C2960XR-48LPD-I WS-C2960XR-48FPD-I	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM CWDM-SFP	15.0(2)EX1	15.0(2)EX1

Table 4 Catalyst 2900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2970 series	WS-C2970G-24TS-E	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-SX-MMD GLC-LH-SMD	—	12.1(14)EA1
Catalyst 2975 Series	WS-C2975GS-48PS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD	—	12.2(46)EX

Table 5 Catalyst 3500 Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3500XL Series	WS-C3508G-XL-EN	WS-G5482	—	12.0(5)XW
	WS-C3512-XL-EN	WS-G5483	—	12.0(5)WC3b
	WS-C3524-XL-EN	WS-G5484		
	WS-C3524-PWR-XL-EN	WS-G5486		
	WS-C3548-XL-EN	WS-G5487		
		CWDM GBIC		
Catalyst 3550 Series	WS-C3550-24-SMI	WS-G5482	—	12.1(6)EA1a
	WS-C3550-24-EMI	WS-G5483	—	12.1(8)EA1b
	WS-C3550-24-DC-SMI	WS-G5484		
		WS-G5486		
		WS-G5487		
		CWDM GBIC	—	12.1(12c)EA1
		DWDM GBIC	—	12.1(20)EA2
	WS-C3550-24-FX-SMI	WS-G5482	—	12.1(12c)EA1
	WS-C3550-24PWR-SMI	WS-G5483		
	WS-C3550-24PWR-EMI	WS-G5484		
		WS-G5486		
		WS-G5487		
		CWDM GBIC		
		DWDM GBIC	—	12.1(20)EA2

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3550 Series (continued)	WS-C3550-48-SMI WS-C3550-48-EMI	WS-G5482	—	12.1(8)EA1b
		WS-G5483		
		WS-G5484 WS-G5486 WS-G5487		
		CWDM GBIC	—	12.1(12c)EA1
		DWDM GBIC	—	12.1(20)EA2
	WS-C3550-12G WS-C3550-12T	WS-G5482	—	12.1(6)EA1
		WS-G5483 WS-G5484 WS-G5486 WS-G5487	—	12.1(8)EA1b
		CWDM GBIC	—	12.1(12c)EA1
		DWDM GBIC	—	12.1(20)EA2
Catalyst 3560 Series	WS-C3560-24PS WS-C3560-48PS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.1(19)EA1c
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(19)EA1c
	GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB	
	DWDM SFP	12.2(46)SE	12.2(40)SE	
	DWDM SFP (add.)	12.2(52)SE	12.2(52)SE	

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560 Series (continued)	WS-C3560G-24TS WS-C3560G-48TS WS-C3560G-48PS WS-C3560G-24PS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(20)SE3
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(20)SE3
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3560-48TS WS-C3560-24TS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(20)SE3
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(20)SE3
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3560-8PC	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(35)SE
		GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(35)SE

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560 Series (continued)	WS-C3560-12PC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(46)SE
		GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(46)SE
	WS-C3560V2-24PS WS-C3560V2-24TS WS-C3560V2-48PS WS-C3560V2-48TS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(50)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L CWDM SFP GLC-BX-D GLC-BX-U DWDM SFP	12.2(50)SE	12.2(50)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560-E Series	WS-C3560E-24TD WS-C3560E-24PD WS-C3560E-48TD WS-C3560E-48PD WS-C3560E-48PDF With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000)	—	12.2(35)SE2
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(35)SE2
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
		GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(40)EX
	WS-C3560E-12D With CVR-X2-SFP (for X2 ports)	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(40)EX
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560-E Series (continued)	WS-C3560E-12SD	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(44)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(44)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
		WS-C3560E-12SD With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—
	WS-C3560E-12SD With CVR-X2-SFP (for X2 ports)	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(44)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560-X Series	WS-C3560X-24T WS-C3560X-48T WS-C3560X-24P WS-C3560X-48P WS-C3560X-48PF With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-T (10/100/1000)	—	12.2(53)SE
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
	WS-C3560X-24T WS-C3560X-48T WS-C3560X-24P WS-C3560X-48P WS-C3560X-48PF With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MM GLC-LH-SM	—	12.2(53)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 5 Catalyst 3500 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3560-C Series	WS-C3560CG-8TC-S WS-C3560CG-8PC-S	GLC-SX-MM	—	12.2(55)EX
		GLC-SX-MMD		
		GLC-LH-SM		
	WS-C3560C-8PC-S WS-C3560C-12PC-S	GLC-LH-SMD	—	12.2(55)EX3
		GLC-ZX-SM		
		GLC-ZX-SMD		
WS-C3560C-8PC-S WS-C3560C-12PC-S	GLC-BX-D	—	15.0(2)SE	
	GLC-BX-U			
	CWDM SFP			
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	—	15.0(2)SE

Table 6 Catalyst 3600 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3650 Series	WS-C3650-24TS	GLC-T (10/100/1000)	XE 3.3.0SE	XE 3.3.0SE
	WS-C3650-48TS	GLC-LH-SM		
	WS-C3650-24PS	GLC-LH-SMD		
	WS-C3650-48PS	GLC-SX-MM		
	WS-C3650-48FS	GLC-SX-MMD		
	WS-C3650-24TD	GLC-EX-SMD		
	WS-C3650-48TD	(CPN 10-2624-01 or later only)		
	WS-C3650-24PD	GLC-ZX-SM		
	WS-C3650-48PD	GLC-ZX-SMD		
	WS-C3650-48FD	GLC-BX-D		
	WS-C3650-48FQ	GLC-BX-U		
	WS-C3650-48PQ	CWDM SFP		
	WS-C3650-48TQ	SFP-GE-S		
		SFP-GE-L		
		SFP-GE-T		
	SFP-GE-Z			
	DWDM SFP			
	DWDM SFP (add.)			

Table 7 Catalyst 3700 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750 series	WS-C3750G-12S WS-C3750G-24TS WS-C3750G-48TS WS-C3750G-24PS WS-C3750G-48PS	GLC-T (10/100/1000)	—	12.1.(14)EA1
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(14)EA1
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3750-24TS WS-C3750-48TS	GLC-T (10/100/1000)	—	12.1(14)EA1
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD	12.2(46)SE	12.1(14)EA1
		GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(19)EA1c
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE

Table 7 Catalyst 3700 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			DOM Support	Cisco IOS Release	
Catalyst 3750 series (continued)	WS-C3750-24PS WS-C3750-48PS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.1(19)EA1c	
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(19)EA1c	
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB	
		DWDM SFP	12.2(46)SE	12.2(40)SE	
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE	
		WS-C3750-24FS-S	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(25)SEB
			GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
			DWDM SFP	12.2(46)SE	12.2(40)SE
			DWDM SFP (add.)	12.2(52)SE	12.2(52)SE

Table 7 Catalyst 3700 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750 series (continued)	WS-C3750-24WFS	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	—	12.2(25)FZ
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)FZ
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3750V2-24PS WS-C3750V2-24TS WS-C3750V2-48PS WS-C3750V2-48TS WS-C3750V2-24FS (uplink ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(50)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U DWDM SFP	12.2(50)SE	12.2(50)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 7 Catalyst 3700 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750-E Series	WS-C3750E-24TD WS-C3750E-24PD WS-C3750E-48TD WS-C3750E-48PD WS-C3750E-48PDF With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(35)SE2
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(35)SE2
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3750-X Series	WS-C3750X-24T WS-C3750X-48T WS-C3750X-24P WS-C3750X-48P WS-C3750X-48PF With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	—	12.2(53)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 7 Catalyst 3700 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750-X Series (continued)	WS-C3750X-24T	GLC-SX-MM	—	12.2(53)SE
	WS-C3750X-48T	GLC-LH-SM	—	12.2(53)SE
	WS-C3750X-24P	GLC-SX-MMD	12.2(53)SE	12.2(53)SE
	WS-C3750X-48P	GLC-LH-SMD	12.2(53)SE	12.2(53)SE
	WS-C3750X-48PF	GLC-ZX-SM	12.2(53)SE	12.2(53)SE
	With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-ZX-SMD	12.2(53)SE	12.2(53)SE
		GLC-BX-D	12.2(53)SE	12.2(53)SE
		GLC-BX-U	12.2(53)SE	12.2(53)SE
		CWDM SFP	12.2(53)SE	12.2(53)SE
		SFP-GE-S	12.2(53)SE	12.2(53)SE
SFP-GE-L		12.2(53)SE	12.2(53)SE	
	SFP-GE-Z	12.2(53)SE	12.2(53)SE	
	DWDM SFP	12.2(53)SE	12.2(53)SE	
	DWDM SFP (add.)	12.2(53)SE	12.2(53)SE	
	GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE	
WS-C3750X-12S WS-C3750X-24S Client ports and uplink ports with C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-T (10/100/1000)	GLC-SX-MM	—	12.2(55)SE5
	GLC-LH-SM	GLC-LH-SM	—	12.2(55)SE5
	GLC-SX-MMD	GLC-LH-SMD	12.2(55)SE5	12.2(55)SE5
		GLC-ZX-SM	12.2(55)SE5	12.2(55)SE5
		GLC-ZX-SMD	12.2(55)SE5	12.2(55)SE5
		GLC-BX-D	12.2(55)SE5	12.2(55)SE5
		GLC-BX-U	12.2(55)SE5	12.2(55)SE5
		CWDM SFP	12.2(55)SE5	12.2(55)SE5
		SFP-GE-S	12.2(55)SE5	12.2(55)SE5
		SFP-GE-L	12.2(55)SE5	12.2(55)SE5
	SFP-GE-Z	12.2(55)SE5	12.2(55)SE5	
	DWDM SFP	12.2(55)SE5	12.2(55)SE5	
	DWDM SFP (add.)	12.2(55)SE5	12.2(55)SE5	
	GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE	

Table 7 Catalyst 3700 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750-X Series (continued)	WS-C3750X-12S WS-C3750X-24S	GLC-SX-MM GLC-LH-SM	—	12.2(55)SE5
	Uplink ports with C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(55)SE5	12.2(55)SE5
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 8 Catalyst 3800 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3850 Series	C3850-NM-4-1G C3850-NM-2-10G C3850-NM-4-10G	GLC-T (10/100/1000) GLC-LH-SM GLC-LH-SMD GLC-SX-MM GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)	XE 3.2.0SE	XE 3.2.0SE

Table 9 Industrial Ethernet and Smart Grid Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Cisco IE2000 series	IE-2000-4TS-G-L	GLC-SX-MM-RGD	—	15.0(1)EY
	IE-2000-4TS-G-B	GLC-LX-SM-RGD		
	IE-2000-4T-G-L	GLC-ZX-SM-RGD		
	IE-2000-4T-G-B	SFP-GE-S		
	IE-2000-8TC-G-L	SFP-GE-L		
	IE-2000-8TC-G-B	SFP-GE-Z		
	IE-2000-8TC-G-E	GLC-SX-MM ¹		
	IE-2000-8TC-G-N	GLC-LH-SM ¹		
	IE-2000-16TC-G-L	GLC-SX-MMD		
	IE-2000-16TC-G-E	GLC-LH-SMD		
	IE-2000-16TC-G-X	GLC-EX-SMD		
	IE-2000-16TC-G-N	GLC-BX-D ²		
	IE-2000-16PTC-G-L	GLC-BX-U ²		
	IE-2000-16PTC-G-E	CWDM SFP ²		
	IE-2000-16PTC-G-NX	DWDM SFP ² DWDM SFP (add.) ²		
Cisco IE2000U series	IE 2000U-4TS-G	GLC-SX-MM-RGD	—	15.0(2)EH
	IE 2000U-8TC-G	GLC-LX-SM-RGD		
	IE 2000U-16TC-G	GLC-ZX-SM-RGD		
	IE 2000U-16TC-G-X	GLC-BX-D		
	IE 2000U-16TC-GP	GLC-BX-U		
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-EX-SMD CWDM-SFP		
Cisco IE3000 series	IE-3000-4TC	GLC-SX-MM-RGD	—	12.2(44)EX
	IE-3000-8TC	GLC-LX-SM-RGD		
		GLC-ZX-SM-RGD		
		GLC-BX-D	—	12.2(50)SE
		GLC-BX-U		
		CWDM SFP		
	GLC-LH-SMD	—	15.0(2)SE	
	GLC-EX-SMD			
	GLC-ZX-SMD			

Table 9 Industrial Ethernet and Smart Grid Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Cisco IE3010 series	IE-3010-24TC IE-3010-16S-8PC	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-SX-MMD	—	12.2(53)EZ
		GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	—	15.0(2)SE
Cisco 2500 Connected Grid Switch Series	CGS-2520-24TC CGS-2520-16S-8PC	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L GLC-EX-SMD SFP-GE-Z CWDM SFP	—	12.2(53)EX
Cisco 2000 Connected Grid Router Series	CGR 2010	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	—	15.1(1)T

1. Only Version -03 or later is supported.
2. Only Version -02 or later is supported.

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series	WS-X4013	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CDWM GBIC	—	—
	WS-X4013+	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CDWM GBIC	12.1(19)EW	—
		DWDM GBIC	12.1(19)EW	12.1(19)EW
	WS-X4013+TS	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(20)EWA	—
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	WS-X4013+10GE	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(25)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(25)SG	12.2(25)SG
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series (continued)	WS-X4748-SFP-E WS-X4724-SFP-E WS-X4712-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-LH-SMD GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP	15.2(1)E	15.2(1)E
	WS-X4014	WS-G5483	12.1(13)EW	—
	WS-X4232-GB-RJ WS-X4306-GB WS-X4412-2GB-T	WS-G5484 WS-G5486 WS-G5487	12.1(8a)EW	—
		CWDM GBIC	12.1(12c)EW	—
		DWDM GBIC	12.1(19)EW	12.1(19)EW

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series (continued)	WS-X4418-GB	WS-G5484 WS-G5486 WS-G5487	12.1(8a)EW	—
		CWDM GBIC	12.1(12c)EW	—
		DWDM GBIC	12.1(19)EW	12.2(19)EW
	WS-X4302-GB	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.1(19)EW	—
		DWDM GBIC	12.1(19)EW	12.2(19)EW
	WS-X4448-GB-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(20)EW	—
		CWDM SFP	12.2(20)EW	12.2(20)EW
		GLC-BX-D GLC-BX-U	12.2(20)EWA	12.2(20)EWA
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(25)EWA 10	12.2(25)EWA 10
	WS-X4506-GB-T	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(20)EWA	—
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			Cisco IOS Support	DOM Support	
Catalyst 4500 series (continued)	WS-X4515	WS-G5483	12.1(13)EW	—	
		WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.1(12c)EW	—	
		DWDM GBIC	12.1(19)EW	12.1(19)EW	
		WS-X4516	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.2(18)EW	—
	DWDM GBIC		12.2(18)EW	12.2(18)EW	
	WS-X4516-10GE		GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(25)EWA	—
			GLC-BX-D GLC-BX-U CWDM SFP	12.2(25)EWA	12.2(25)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG	
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3	
		GLC-ZX-SMD	12.2(25)EWA 10	12.2(25)EWA 10	
		WS-X45-SUP6-E WS-X4606-X2 with CVR-X2-SFP Twin Gig converter	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(40)SG	—
	GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP		12.2(40)SG	12.2(40)SG	
	DWDM SFP (add.)		12.2(53)SG3	12.2(53)SG3	
	GLC-EX-SMD (CPN 10-2624-01 or later only)		15.1(1)SG	15.1(1)SG	
	GLC-ZX-SMD		12.2(40)SG	12.2(40)SG	

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series (continued)	WS-X4624-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(44)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(44)SG	12.2(44)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(44)SG1	12.2(44)SG1
		WS-X45-SUP6L-E with CVR-X2-SFP Twin Gig converter	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(52)SG
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(52)SG	12.2(52)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD GLC-ZX-SMD	15.1(1)SG	15.1(1)SG

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series (continued)	WS-X4612-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(54)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(54)SG	12.2(54)SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(44)SG1	12.2(44)SG1
	WS-X4640-CSFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	15.0(2)SG	—
		GLC-BX-D GLC-2BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-ZX-SMD	15.0(2)SG	15.0(2)SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			Cisco IOS Support	DOM Support	
Catalyst 4500 series (continued)	WS-X4712-SFP+E WS-X45-SUP7-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	3.1.0SG	—	
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.1.0SG	3.1.0SG	
		GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	3.4.1SG	3.4.1SG	
	WS-X45-SUP7L-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	3.2.0XO	—	
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.2.0XO	3.2.0XO	
		GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	3.4.1SG	3.4.1SG	
	Catalyst 4500 series (continued)	WS-X45-SUP8-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD	3.3.0XO	—
			GLC-LH-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	3.3.0XO	3.3.0XO

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500-X Series	WS-C4500X-32SFP+ WS-C4500X-F-32SFP+ WS-C4500X-40X-ES C4KX-NM-8SFP+	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	3.3.0SG	—
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.3.0SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.3.0SG	3.3.0SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	3.4.1SG	3.4.1SG
	WS-C4500X-16SFP+ WS-C4500X-F-16SFP+ WS-C4500X-24X-ES	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	3.3.1(SG	—
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.3.1SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.3.1SG	3.3.1SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	3.4.1SG	3.4.1SG

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4900 Series	WS-C4912G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	—
	WS-C4948	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SMD	12.2(20)EWA	—
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM (add.)	12.2(53)SG3	12.2(53)SG3
	WS-4928-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(46)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(46)SG	12.2(46)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4900 Series (continued)	WS-C4948E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(54)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(54)SG	12.2(54)SG
		DWDM SFP (add.) GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	12.2(53)SG3	12.2(53)SG3
	WS-X4908 with CVR-X2-SFP Twin Gig converter in a WS-C4900M	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(40)X0 or 12.2(44)SG	—
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(40)X0 or 12.2(44)SG	12.2(40)X0 or 12.2(44)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(40)XO	12.2(40)XO

Table 11 Catalyst 6500 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			Catalyst Operating System	Cisco IOS Release	DOM Support
Catalyst 6500 Series	WS-X6K-SUP1-2GE WS-X6K-SUP1A-2GE WS-X6K-SUP1A-MSFC WS-X6K-SUP1A-MSFC2 WS-X6K-SUP1A-PFC WS-X6K-SUP2U-MSFC2 WS-X6K-S2-PFC2	WS-G5483	7.2	12.1(13)E	—
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	—
		CWDM GBIC	7.2	12.1(13)E	—
	WS-X6K-SUP2-MSFC2 WS-X6K-SUP2U-PFC2 WS-X6408-GBIC WS-X6408A-GBIC WS-X6416-GBIC WS-X6516-GBIC WS-X6816-GBIC	WS-G5483	7.2	12.1(13)E	—
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	—
		CWDM GBIC	7.2	12.1(13)E	—
		DWDM GBIC	8.3.1	12.2(17a)SX	—
	WS-X6516A-GBIC	WS-G5483	7.5.1	12.1(19)E1	—
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	—
		CWDM GBIC	7.5.1	12.1(19)E1	—
		DWDM GBIC	8.3.1	12.2(17a)SX	—
	WS-SUP720	GLC-T(1000BASE-T)	8.3.1	12.2(17a)SX	—
		GLC-SX-MM			
		GLC-LH-SM	8.1.1	12.2(14)SX	—
		GLC-ZX-SM	8.1.1	12.2(17a)SX	—
		GLC-BX-D	8.2	12.2(17d)SXB1	—
		GLC-BX-U	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		CWDM SFP	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		DWDM SFP ¹	8.3.1	12.2(17a)SX	12.2(18)SXE
		GLC-SX-MMD	—	12.2(33)SXH	12.2(33)SXH
GLC-LH-SMD		—	12.2(14)SX	—	
GLC-ZX-SMD	—	12.2(17a)SX	—		

Table 11 Catalyst 6500 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			Catalyst Operating System	Cisco IOS Release	DOM Support
Catalyst 6500 Series (continued)	WS-SUP720-3B WS-SUP720-3BXL	GLC-T (1000BASE-T)	8.3.2	12.2(17d)SXB1	—
		GLC-SX-MM	8.3.2	12.2(17d)SXB1	—
		GLC-LH-SM	8.3.2	12.2(17d)SXB1	—
		GLC-ZX-SM	8.3.2	12.2(17d)SXB1	—
		GLC-BX-D	8.3.2	12.2(17d)SXB1	—
		GLC-BX-U	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		CWDM SFP	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		DWDM SFP ¹	8.3.2	12.2(17d)SXB1	12.2(18)SXE
		GLC-SX-MMD	—	12.2(33)SXH	12.2(33)SXH
		GLC-LH-SMD	—	12.2(17d)SXB1	—
		GLC-ZX-SMD	—	12.2(17d)SXB1	—
		WS-SUP32-GE-3B WS-SUP32-10GE-3B	GLC-T (1000BASE-T)	8.4(1)	12.2(18)SXF
	GLC-SX-MM		8.4(1)	12.2(18)SXF	—
	GLC-LH-SM		8.4(1)	12.2(18)SXF	—
	GLC-ZX-SM		8.4(1)	12.2(18)SXF	—
	GLC-BX-D		8.4(1)	12.2(18)SXF	—
	GLC-BX-U		8.4(1)	12.2(18)SXF	12.2(18)SXF
	CWDM SFP		8.4(1)	12.2(18)SXF	12.2(18)SXF
	DWDM SFP ¹		8.4(1)	12.2(18)SXF	12.2(18)SXF
	GLC-SX-MMD		—	12.2(33)SXH	12.2(33)SXH
	GLC-LH-SMD		—	12.2(18)SXF	—
	GLC-ZX-SMD		—	12.2(18)SXF	—
	WS-SUP32-GE-PISA		GLC-T (1000BASE-T)	—	12.2(18)ZY
		GLC-SX-MM			
		GLC-LH-SM			
		GLC-ZX-SM			
		GLC-BX-D			
		GLC-BX-U			
		CWDM SFP			
		DWDM SFP ¹			
	GLC-SX-MMD				
	GLC-LH-SMD				
	GLC-ZX-SMD				

Table 11 Catalyst 6500 Series Switches Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			Catalyst Operating System	Cisco IOS Release	DOM Support
Catalyst 6500 Series (continued)	VS-S720-10G-3C VS-S720-10G-3CXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP ¹ GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(33)SXH	— — — — 12.2(33)SXH 12.2(33)SXH 12.2(33)SXH 12.2(33)SXH — —
	WS-X6724-SFP WS-X6748-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP ¹ GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	8.3.1 8.1.1 8.1.1 8.2 8.4.1 8.4.1 8.3.1 — — —	12.2(17a)SX 12.2(14)SX 12.2(17a)SX 12.2(17d)SXB1 12.2(18)SXE1 12.2(18)SXE1 12.2(17a)SX 12.2(33)SXH- 12.2(14)SX 12.2(17a)SX	—
Catalyst 6500 Series (continued)	VS-S2T-10G VS-S2T-10G-XL WS-X6824-SFP-2T WS-X6824-SFP-2TXL WS-X6848-SFP-2T WS-X6848-SFP-2TXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ¹ GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(50)SY	—
	WS-X6904-40G-2T WS-X6904-40G-2TXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ¹ GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(1)SY	—

1. Does not include support for the DWDM SFP transceivers (8 additional wavelengths). See Table 1 for specific model numbers.

Table 12 Catalyst 6800 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 6800 Series	C6800IA-48FPD C6800IA-48TD	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-T GLC-SX-MM	15.1(2)SY2	15.1(2)SY2
	C6880-X	GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM	15.1(2)SY1	15.1(2)SY1

Table 13 Data Center and Blade Switching Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco Catalyst 2350 Series	2350-48TD-S 2350-48TD-SD (with CVR-X2-SFP TwinGig converter)	GLC-T GLC-SX-MM GLC-SX-MMD	—	Cisco IOS 12.2(46)EY
Cisco Catalyst 2360 Series	2360-48TD-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	Cisco IOS 12.2(53)EY

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco Catalyst 3000 and 3100 Blade Switches	WS-CBS3020-HPQ	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	Cisco IOS 12.2(35)SE
	WS-CBS3030-DEL WS-CBS3040-FSC	GLC-T (1000BASE-T) GLC-SX-MM GLC-SX-MMD	—	Cisco IOS 12.2(35)SE
	WS-CBS-3120G-S WS-CBS-3130G-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	Cisco IOS 12.2(40)EX1
	WS-CBS3032-DEL (with CVR-X2-SFP TwinGig converter)	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	Cisco IOS 12.2(40)EX1
	WS-CBS3110X-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	Cisco IOS 12.2(52)SE
Cisco Nexus 2000 Series	N2K-C2232PP-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	NX-OS 4.2(1)N2(1)
Cisco Nexus 3000 Series	N3K-C3064PQ	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	NX-OS 5.0(3)U1(1d)
	N3K-C3064PQ-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	NX-OS 5.0(3)U1(2)
	N3K-C3048TP-1GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	NX-OS 5.0(3)U2(2b)

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco Nexus 4000 Series	N4K-4001I-XPX	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	NX-OS 4.1(2)E1(1)
Cisco Nexus 5000 Series	N5K-C5010P-BF N5K-C5020P-BF	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM SFP-GE-T (1000BASE-T)	—	NX-OS 4.0(1a)N1(1)
		SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	NX-OS 4.0(1a)N1(1)	NX-OS 4.0(1a)N1(1)
	N5K-C5548P-FA N5K-C5548UP-FA N5KC5596UP-FA N55-M16P N55-M8P8FP N55-M16UP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM SFP-GE-T (1000BASE-T)	—	NX-OS 5.0(3)N1(1B)
		SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	NX-OS 5.0(3)N1(1B)	NX-OS 5.0(3)N1(1B)
Cisco Unified Computing System	N10-S6100 N10-S6200 N10-E0440 N10-E0600 N20-I6584	SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	UCS Manager v1.3	UCS Manager v1.3
		GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	—	UCS Manager v1.3
	UCS-FI-6248UP UCS-FI-E16UP UCS-IOM-2208XP	SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	UCS Manager v2.0(1)	UCS Manager v2.0(1)
		GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	—	UCS Manager v2.0(1)

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco Nexus 7000 Series	N7K-M148GS-11	SFP-GE-S	NX-OS 4.1(2)	NX-OS 4.1(2)
		GLC-SX-MMD	NX-OS 4.1(2)	
		GLC-SX-MM	—	
		SFP-GE-L	NX-OS 4.1(2)	
		GLC-LH-SMD	NX-OS 4.1(2)	
		GLC-LH-SM	—	
		SFP-GE-Z	NX-OS 4.1(2)	
		GLC-ZX-SM	—	
		GLC-T (1000BASE-T)	—	NX-OS 4.2(1)
		SFP-GE-T (1000BASE-T)	—	
		CWDM SFP	—	
		DWDM SFP	NX-OS 4.2(1)	
			NX-OS 4.2(1)	
		GLC-BX-D	NX-OS 5.2(1)	NX-OS 5.2(1)
		GLC-BX-U	NX-OS 5.2(1)	
		GLC-EX-SMD	NX-OS 6.2(2)	NX-OS 6.2(2)
		GLC-ZX-SMD		

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			DOM support	Cisco IOS or NX-OS Release	
Cisco Nexus 7000 Series (continued)	N7K-M148GS-11L	SFP-GE-S	NX-OS 5.0(2a)	NX-OS 5.0(2a)	
		GLC-SX-MMD	NX-OS 5.0(2a)		
		GLC-SX-MM	—		
		SFP-GE-L	NX-OS 5.0(2a)		
		GLC-LH-SMD	NX-OS 5.0(2a)		
		GLC-LH-SM	—		
		SFP-GE-Z	NX-OS 5.0(2a)		
		GLC-ZX-SM	—		
		GLC-T (1000BASE-T)	—		
		SFP-GE-T (1000BASE-T)	—		
	CWDM SFP	NX-OS 5.0(2a)			
	DWDM SFP	NX-OS 5.0(2a)			
	N7K-F132XP-15	GLC-BX-D GLC-BX-U	GLC-BX-D	NX-OS 5.2(1)	NX-OS 5.2(1)
			GLC-BX-U	NX-OS 5.2(1)	
GLC-EX-SMD GLC-ZX-SMD			NX-OS 6.2(2)	NX-OS 6.2(2)	
N7K-F132XP-15	GLC-SX-MMD GLC-SX-MM SFP-GE-L GLC-LH-SMD GLC-LH-SM SFP-GE-Z GLC-ZX-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	SFP-GE-S	NX-OS 5.1(1)	NX-OS 5.1(1)	
		GLC-SX-MMD	NX-OS 5.1(1)		
		GLC-SX-MM	—		
		SFP-GE-L	NX-OS 5.1(1)		
		GLC-LH-SMD	NX-OS 5.1(1)		
		GLC-LH-SM	—		
		SFP-GE-Z	NX-OS 5.1(1)		
		GLC-ZX-SM	—		
		GLC-T (1000BASE-T)	—		
		SFP-GE-T (1000BASE-T)	—		
N7K-F132XP-15	GLC-ZX-SMD	GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2(2)	

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco Nexus 7000 Series (continued)	N7K-F248XP-25	GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	NX-OS 6.0
		GLC-SX-MMD SFP-GE-S GLC-LH-SMD SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	NX-OS 6.0	NX-OS 6.0
		GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2(2)
	N7K-F248XP-25E	GLC-T (1000BASE-T) SFP-GE-T(1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	NX-OS 6.1(2)
		GLC-SX-MMD SFP-GE-S GLC-LH-SMD SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	NX-OS 6.1(2)	NX-OS 6.1(2)
		GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2(2)
Cisco Nexus 9000 Series	N9K-C93128TX N9K-C9396PX N9K-X9564PX N9K-X9636PQ N9K-X9564TX	GLC-SX-MMD GLC-LH-SMD	6.1(2)I1(1)	6.1(2)I1(1)

Table 13 Data Center and Blade Switching Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM support	Cisco IOS or NX-OS Release
Cisco CSS 11500 Series	CSS11506-2AC CSS11506-2DC CSS11503-AC CSS11503-DC CSS11501 CSS5-SCM-2GE CSS5-IOM-2GE	GLC-T GLC-SX-MM GLC-LH-SM	—	WebNS 7.5
Cisco MDS 9000 Series	Please refer to: http://www/en/US/prod/collateral/ps4159/ps6409/ps4358/product_data_sheet09186a00801bc698.html			

Table 14 Router Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 892F Series	CISCO892F-K9 CISCO892FW-K9	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(2)T
Cisco 1921 Series Router	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M2
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(4)M

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 1941 Series Router	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(4)M
Cisco 2600 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC GLC-ZX-SMD	—	12.2(11)YT
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(25)EZ

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 2800 Series Router	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(25)EZ
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.3(8)T4
Cisco 2900 Series Router	Cisco 2921 Cisco 2951	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 2900 Series Router (continued)	SM-D-ES3G-48-P SM-D-ES3-48-P SM-D-ES2-48	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(4)M
Cisco 3200 Series Rugged Routers	Cisco 3270	GLC-SX-MM-RGD GLC-LX-SM-RGD	—	12.4(6)XE
Cisco 3600 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	12.2(11)YT
Cisco 3700 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	12.2(11)YT
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	—	12.2(25)EZ

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 3800 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	12.2(11)YT
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(25)EZ
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.3(8)T4
	Cisco 3825	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.3(11)T
	Cisco 3845	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.3(11)T

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 3900 Series Router	Cisco 3925 Cisco 3945	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	SM-D-ES3G-48-P SM-D-ES3-48-P SM-D-ES2-48	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.0(1)M
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	15.1(4)M

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 4400 Series Router	Cisco 4451-X	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP	—	XE 3.9.1
		GLC-LH-SMD GLC-SX-MMD	—	XE 3.1.0
		GLC-ZX-MMD	—	XE 3.1.1
Cisco 6400 Universal Access Router	C6400-NRP-2SV	WS-G5484 WS-G5486 WS-G5487	—	12.2(2)B6
Cisco 7200 Series Router The Cisco 7200 series router supports multiple parallel release branches. Where several releases are grouped together, they provide support for all transceivers in the corresponding group.	NPE-G1	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	12.0(28)S 12.1(14)E 12.2(15)B 12.2(4)BW 12.2(14)S 12.2(14)SU 12.2(15)T9
	Cisco 7201	GLC-SX-MM GLC-SX-MMD	—	12.2(33)SRC2 12.4(15)T7 12.4(20)T1
		SFP-GE-T	—	12.2(33)SRC2 12.4(15)T7
		SFP-GE-S SFP-GE-L GLC-LH-SMD SFP-GE-Z CWDM SFP	—	12.2(31)SB2 12.2(33)SRC2 12.4(15)T7
	NPE-G2	GLC-SX-MM GLC-SX-MMD	—	12.2(33)SRC2 12.4(15)T7 12.4(20)T1
		SFP-GE-S SFP-GE-L GLC-LH-SMD SFP-GE-Z CWDM SFP	—	12.2(31)SB2 12.2(33)SRC2 12.4(15)T7
	C7200-I/O-GE+E	WS-G5484 WS-G5486 WS-G5487	—	12.0(14)S2 12.1(3a)E5 12.1(5)T1
	PA-GE	WS-G5484 WS-G5486 WS-G5487	—	12.0(7)S 12.0(6)T 12.1(1)E

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco uBR7200 Series	uBR7200-NPE-G1	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	—	12.2(11)CX
	uBR7200-NPE-G2	GLC-SX-MMD GLC-LH-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP	12.2SB	12.2SB
Cisco 7300 Series Router	CISCO7301	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(18)S1
	7300-NSE-100	WS-G5484 WS-G5486 WS-G5487	—	12.2(20)S
		WS-G5483 CWDM GBIC	—	12.2(28)SB
	7304-NPE-G100	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP	—	12.2(20)S
	7300-NSE-150	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	12.2(31)SB2
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP	12.2(31)SB2	12.2(31)SB2
Cisco 7500 Series Router	GEIP	WS-G5484	—	Please see release notes
	GEIP+	WS-G5486 WS-G5487		

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 7600 Series Router	OSM-1CHOC12/T1-SI	WS-G5484	—	Please see release notes
	OSM-1CHOC12/T3-SI	WS-G5486		
	OSM-2OC12-ATM-MM	WS-G5487		
	OSM-2OC12-ATM-SI	CWDM GBIC		
	OSM-2OC12-ATM-MM+			
	OSM-2OC12-ATM-SI+			
	OSM-4OC3-POS-SI			
	OSM-4OC3-POS-SI+			
	OSM-4OC12-POS-SI			
	OSM-4OC12-POS-SI+			
	OSM-8OC3-POS-MM			
	OSM-8OC3-POS-SI			
	OSM-8OC3-POS-SL			
	OSM-8OC3-POS-SL+			
	OSM-8OC3-POS-SI+			
	OSM-16OC3-POS-MM			
	OSM-16OC3-POS-SI			
	OSM-16OC3-POS-SL			
	OSM-16OC3-POS-SI+			
	OSM-2OC12-POS-MM			
	OSM-2OC12-POS-SI			
	OSM-2OC12-POS-SL			
	OSM-2OC12-POS-SI+			
	OSM-2OC12-POS-MM+			
	OSM4OC12-POS-MM			
	OSM4OC12-POS-SI			
	OSM4OC12-POS-SL			
	OSM4OC12-POS-SI+			
	OSM-1OC48-POS-SI			
	OSM-1OC48-POS-SL			
	OSM-1OC48-POS-SS			
	OSM-1OC48-POS-SS+			
	OSM-10C48-POS-SI+			
	OSM-1OC48-POS-SL+			
OSM-2OC48/1DPT-SS				
OSM-2OC48/1DPT-SI				
OSM-2OC48/1DPT-SL				
OSM-2+4GE-WAN+				
OSM-4GE-WAN-GBIC				

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 7600 Series Router (continued)	WS-SUP720 WS-SUP720-3B WS-SUP720-3BXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(33)SRA
		CWDM SFP	12.2(33)SRA	12.2(33)SRA
	WS-SUP32-GE-3B	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(33)SRA
		GLC-BX-D GLC-BX-U	12.2(33)SRA	12.2(33)SRA
		CWDM SFP	12.2(33)SRB	12.2(33)SRB
		DWDM SFP	12.2(33)SRE	12.2(33)SRE
	WS-X6724-SFP WS-X6748-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	—	12.2(33)SRA
		SFP-GE-T (1000BASE-T) SFP-GE-S SFP-GE-L SFP-GE-Z	—	12.2(33)SRB
		DWDM SFP	—	12.2(33)SRE

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 7600 Series Router (continued)	RSP720-3C-GE RSP720-3CXL-GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	12.2(33)SRB
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRE1	12.2(33)SRB
		SFP-GE-T (1000BASE-T)	—	12.2(33)SRE1
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L	12.2(33)SRE1	12.2(33)SRE1
	RSP720-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM SFP-GE-T (1000BASE-T)	—	12.2(33)SRC
		GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRC	12.2(33)SRC
		CWDM SFP DWDM SFP	12.2(33)SRE1	12.2(33)SRE1
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRB	12.2(33)SRB
	7600-ES20-GE3CXL 7600-ES20-GE3C	SFP-GE-T CWDM SFP	— 12.2(33)SRB3	12.2(33)SRB3
		GLC-BX-D GLC-BX-U DWDM SFP	12.2(33)SRD	12.2(33)SRD
		DWDM SFP (add.)	12.2(33)SRE	12.2(33)SRE

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required		
			DOM Support	Cisco IOS Release	
Cisco 7600 Series Router (continued)	7600-ES+20G3C 7600-ES+20G3CXL 7600-ES+40G3C 7600-ES+40G3CXL	SFP-GE-T	—	12.2(33)SRD	
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(33)SRD	12.2(33)SRD	
		DWDM SFP (add.)	12.2(33)SRE	12.2(33)SRE	
	76-ES+T-20G 76-ES+T-40G	SFP-GE-T	—	12.2(33)SRD3	
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(33)SRD3	12.2(33)SRD3	
			DWDM SFP (add.)	12.2(33)SRE	12.2(33)SRE
	76-ES+XC-20G3C 76-ES+XC-20G3CXL 76-ES+XC-40G3C 76-ES+XC-40G3CXL	SFP-GE-T	—	12.2(33)SRE	
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(33)SRE	12.2(33)SRE	
			DWDM SFP (add.)		

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 10000 Series Router	ESR-1GE	WS-G5484 WS-G5486 WS-G5487	—	Please see release notes
	ESR-HH-1GE	SFP-GE-T	—	12.0(23)S
		SFP-GE-S SFP-GE-L SFP-GE-Z	12.0(23)S	12.0(23)S
Cisco uBR10000 Series Router	UBR10-1GE	WS-G5484 WS-G5486 WS-G5487	—	Please see release notes
	ESR-HH-1GE	SFP-GE-T	—	12.3(13)BC
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z	12.3(13)BC	12.3(13)BC
Cisco RF Gateway Series	RFGW-X4516-10GE	SFP-GE-S SFP-GE-L	12.2(44)SQ	12.2(44)SQ
	RFGW-DS48	SFP-GE-T	—	12.2(44)SQ
		SFP-GE-S SFP-GE-L	12.2(44)SQ	12.2(44)SQ
Cisco 10700 Series Internet Router	10720-GE-FE-TX	SFP-GE-T	—	12.0(27)S
	10720-GE-FE-TX-B	SFP-GE-S SFP-GE-L SFP-GE-Z	12.0(26)S	12.0(26)S
		CWDM SFP	12.0(31)S	12.0(31)S

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 12000 Series Router	10x1GE-SFP-LC-B	GLC-SX-MM GLC-LH-SM	—	12.0(21)S
	4GE-SFP-LC	GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	12.0(25)S
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM SFP		12.0(32)S
EPA-3GE-SX/LH-LC	GLC-SX-MM GLC-LH-SM GLC-ZX-SM	—	12.0(23)S	
Shared Port Adapters (SPAs)	SPA-2X1GE SPA-5X1GE SPA-8X1GE SPA-10X1GE SPA-5X1GE-V2 SPA-8X1GE-V2 SPA-10X1GE-V2	SFP-GE-T SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	SPA software support is determined by the platform on which the SPA is installed. Refer to the SPA release notes for the correct software release.	
	SPA-2X1GE-V2	SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD		

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
CRS Router Series	CRS-16-RP	GLC-LH-SM GLC-LH-SMD	—	XR 2.0
	CRS-16-RP-B	GLC-LH-SM GLC-LH-SMD	—	XR 3.3
	CRS-FCC-SC-22GE	GLC-LH-SM GLC-LH-SMD	—	XR 3.4.1
	42-1GE 20-1GE-FLEX	SFP-GE-T (1000BASE-T)	—	XR 3.8.1
		SFP-GE-S GLC-SX-MMD SFP-GE-L GLC-LH-SMD SFP-GE-Z	XR 3.8.1	XR 3.8.1
CRS-8-PRP-6G CRS-8-PRP-12G	GLC-LH-SM GLC-LH-SMD	—	XR 4.0.2	
ASR 901 Series Router	A901-12C-F-D A901-12-C-FT-D	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD	—	15.1(2)SNG
		SFP-GE-S SFP-GE-L SFP-GE-Z	15.1(2)SNI	15.1(2)SNG
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNI	15.2(2)SNG

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
ASR 901 Series Router (continued)	A901-4C-F-D A901-4-C-FT-D A901-6CZ-F-D A901-6-CZ-FT-D A901-6CZ-F-A A901-6-CZ-FT-A	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD	—	15.2(2)SNH1
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNH1	15.2(2)SNH1
Cisco ASR 903 Series	A900-IMA8S	SFP-GE-T GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	—	XE 3.5.0S
		GLC-BX-D GLC-BX-U GLC-EX-SMD	XE 3.5.0S	XE 3.5.0S
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	XE 3.6.0S	XE 3.6.0S

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
ASR 1000 Series Router	ASR1001	SFP-GE-T	—	XE 2.1
	ASR1002	SFP-GE-S	XE 2.1	XE 2.1
	ASR1002-F	SFP-GE-L		
	ASR1002-X	SFP-GE-Z		
		CWDM SFP		
		DWDM SFP		
		GLC-BX-D GLC-BX-U	XE 2.5	XE 2.5
	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	XE 3.4S	XE 3.4S	
	GLC-EX-SMD	XE 3.5S	XE 3.5S	
	ASR 1000 platform with SPA cards	Software support on the ASR 1000 modular platforms is determined by the platform on which the SPA is installed. Refer to the SPA release notes for the correct software release. http://www.cisco.com/en/US/docs/interfaces_modules/shared_port_adapters/configuration/ASR1000/ASRspasw.pdf		
ASR 9000 Series Router	A9K-40GE-B	SFP-GE-T (10/100/1000)	—	XR 3.7.3
	A9K-40GE-E	SFP-GE-S	XR 3.7.3	XR 3.7.3
		SFP-GE-L		
		SFP-GE-Z		
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP		
	DWDM SFP (add.)	XR 3.9.0	XR 3.9.0	
	GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.1.1	XR 4.1.1	

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
ASR 9000 Series Router (continued)	A9K-2T20GE-B A9K-2T20GE-E A9K-2T20GE-L A9K-40GE-L	SFP-GE-T (10/100/1000)	—	XR 3.9.0
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	XR 3.9.0	XR 3.9.0
		GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.1.1	XR 4.1.1
	A9K-MPA-20X1GE	SFP-GE-T (10/100/1000) GLC-LH-SM	—	XR 4.2.0
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.2.0	XR 4.2.0
		SFP-GE-T (10/100/1000)	—	XR 4.2.1
	A9K-RSP440-TR A9K-RSP440-SE	SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.2.1	XR 4.2.1

Table 14 Router Support (continued)

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
ASR 9000 Series Router (EOBC-supported optics)	ASR-9001 ASR-9001-S	SFP-GE-S	XR 4.2.1	XR 4.2.1
		GLC-SX-MMD GLC-LH-SMD	XR 4.3.0	XR 4.3.0
	ASR-9922-RP-SE ASR-9922-RP-TR	SFP-GE-S GLC-SX-MMD GLC-LH-SMD	XR 4.3.1	XR 4.3.1
		A9K-RSP440-TR A9K-RSP440-SE	SFP-GE-S	XR 4.2.1
	GLC-SX-MMD		XR 4.3.0	XR 4.3.0
	GLC-LH-SMD		XR 4.2.3	XR 4.2.3
ASR9000v Series Router	ASR-9000V-AC ASR-9000V-DC-A ASR-9000V-DC-E	SFP-GE-T SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	XR 5.1.0	XR 5.1.0
		GLC-T	—	XR 4.2.3
Cisco MWR 2941 Mobile Wireless Routers	MWR-2941-DC	GLC-SX-MMD GLC-LH-SMD SFP-GE-S SFP-GE-L SFP-GE-Z	12.4(19)MR1	12.4(19)MR1
		GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	—	12.4(19)MR1
		SFP-GE-T	—	12.4(19)MR3/ 12.2(33)MRA
		CWDM SFP DWDM SFP	12.4(19)MR3/ 12.2(33)MRA	12.4(19)MR3/ 12.2(33)MRA
		GLC-BX-D GLC-BX-U	12.2(33)MRB/ 12.4(20)MRA	12.2(33)MRB/ 12.4(20)MRA
		GLC-EX-SMD	15.1(01)MR	15.1(01)MR

Table 15 Appliance Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
ASA5500 Series appliances	SSM-4GE	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	—	ASA 7.0
NAM 2200 Series appliances	NAM2204-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	—	NAM 4.0

Table 16 Wireless LAN Controllers Support

Platform	Controller or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 5700 WLC Series	AIR-CT5760-25-K9 AIR-CT5760-50-K9 AIR-CT5760-100-K9 AIR-CT5760-250-K9 AIR-CT5760-500-K9 AIR-CT5760-1K-K9 AIR-CT5760-HA-K9	GLC-T (10/100/1000) GLC-LH-SM GLC-LH-SMD GLC-SX-MM GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)	XE 3.2.0SE	XE 3.2.0SE

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as an RSS feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service. Cisco currently supports RSS Version 2.0.

This document is to be used in conjunction with the publications shipped with your chassis.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Copyright © 2004–2014, Cisco Systems, Inc.
All rights reserved. Printed in USA.